


# Technical Information

## Raman Calibration Accessory



## Table of Contents

### **Function and system design ..... 3**

Introduction.....3

Controls and connections.....3

### **Specifications.....4**

Dimensions ..... 4

General ..... 5

---

## Function and system design

---

### Introduction

The Raman Calibration Accessory is used for standardizing Raman instruments and analyzers in terms of both wavelength and intensity. When used in conjunction with the calibration protocol recommended in this manual, it allows different instruments to be standardized such that they generate similar spectra when measuring a given sample. The Raman Calibration Accessory was created specifically for use with Raman instruments and analyzers manufactured by Endress+Hauser.

The Raman Calibration Accessory contains wavelength and intensity reference lamps housed in a compact lamp head. The lamp head is connected to the control unit by a 6-foot (1.8 meter) cable with positive locking, quick connectors at both ends. A diffuser window on the lamp head emits a quasi-lambertian pattern of light that, when properly positioned, fills the numerical aperture of a probe lens, microscope objective, or optical fiber.

Neon lamps in the lamp head provide a wide spectrum of atomic emission lines. These emission lines allow convenient wavelength calibration of a broad range of Raman analyzers that use different laser excitation wavelengths. The software provided with your analyzer is designed for use with this accessory and contains automated features for finding and identifying neon emission lines.

For intensity standardization, a long-life, low-voltage tungsten-halogen lamp provides a factory-characterized spectral output. The primary reference source used in the certification process is a [National Institute of Standards and Technology](#) (NIST) traceable source. The halogen cycle maintains near constant color temperature throughout the operating life of the lamp under constant-current operation. A precision current-regulated power source in the control unit assures consistent spectral output over many hours of operation.

---

### Controls and connections

The controls and connections for the Raman Calibration Accessory are described below.

- **Unit power on/off.** The switch on the power entry module at the back of the control unit activates power to the unit. It is recommended that the Halogen lamp be allowed to warm up for 12.5 minutes for the color temperature of the bulb to fully stabilize prior to its use. The Halogen lamp LED indicator will continue blinking as a visual indicator of bulb warm-up time and will be solid when the warm-up period is complete.
- **Lamp head cable/connector.** The 6-foot (1.8-meter) cable connecting the lamp head and the control unit has opposing connector genders on both ends. The red dot on the cable plugs must be aligned with the red dot on the sockets for mating. The connector locks when mated. Pulling directly on the spring-loaded connector body releases the connection.
- **Halogen lamp on/off.** Press the front panel switch to the right to turn on the halogen intensity lamp and lights the right green LED. The lamp will turn off automatically after 60 minutes. The base unit keeps track of the lamp's elapsed "on" time (to the nearest 0.1 minute). If the lamp time exceeds 450 hours, the LED indicator will be continuously yellow when lit. If lamp time exceeds 500 hours, the LED indicator will be continuously red when lit. These two indications alert you to return the unit to Endress+Hauser for recertification.
- **Neon lamps on/off.** The neon lamps can be lit by pressing the front panel switch to the left. There is no time-out function.
- **Power.** The Raman Calibration Accessory uses a universal input switching power supply and will operate over a line input range of 100–240 VAC 50–60 Hz. Main (line) power connection is made through a standard power cord with universal IEC320 connector. Power consumption is 30 Watt (W) maximum.
- **Fuses.** Fuses are user-replaceable through a "drawer" next to the power switch on the back of the control unit. Always replace with 2 each 250 VAC rated metric (5x20 mm) fuses. For operation at 100–120 VAC or 220–230 VAC, use 2A time lag fuses.

## Specifications

### Dimensions

The height, width, and length of the Calibration Accessory are shown below:




Figure 1. Calibration Accessory dimensions

Name	Description
Height	1.7"
Width	8.3"
Length	10.6"

Table 1. Calibration Accessory dimensions

**General**

The Calibration Accessory specifications are listed below:

<b>Item</b>	<b>Description</b>
Wavelength reference	Neon lamps (2)
Spectral intensity reference	Tungsten-halogen
Data file spectral range for given HCA models	HCA-532: 534.5 to 694.0 nm HCA-785: 790.7 to 1074.5 nm HCA-1000: 1012.6 to 1304.6 nm
Spectral intensity output	< ±0.65%
Spectral intensity output	±2.65%
Total long term spectral uncertainty (at any wavelength)	HCA-532: ±2.85% HCA-785: ±6.05% HCA-1000: ±10%
NIST traceable primary standard	Available upon request
Power source	100–240 VAC 50-60 Hz
Power consumption	30 W maximum
Control unit dimensions	212 x 270 x 43 mm (8.3 x 10.6 x 1.7 in.)
Control unit mass (weight)	1.60 kg (3.5 lbs)
Lamp head dimensions	50 x 80 x 19 mm (2.0 x 3.1 x 0.7 in.)
Lamp head mass (weight)	0.10 kg (0.2 lbs)
CE certified	Yes

*Table 2. Specifications*

[www.addresses.endress.com](http://www.addresses.endress.com)

---