



# IECEX Certificate of Conformity

## INTERNATIONAL ELECTROTECHNICAL COMMISSION IEC Certification System for Explosive Atmospheres

for rules and details of the IECEx Scheme visit [www.iecex.com](http://www.iecex.com)

Certificate No.: **IECEX IBE 20.0031X** Page 1 of 3 [Certificate history:](#)  
Status: **Current** Issue No: 0  
Date of Issue: 2021-06-08  
Applicant: **Endress + Hauser Wetzler GmbH & Co. KG**  
Obere Wank 1  
87484 Nesselwang  
Germany  
Equipment: **NAMUR Switch Isolating Amplifier type RLN22-xx\*\***  
Optional accessory:  
Type of Protection: **intrinsic safety in combination with increased safety and sealed device**  
Marking: **[Ex ia Ga] IIC**  
**[Ex ia Da] IIIC**  
**Ex ec nC [ia Ga] IIC T4 Gc**  
**-40 °C ≤ T<sub>amb</sub> ≤ +60 °C**

Approved for issue on behalf of the IECEx  
Certification Body:

Alexander Henker

Position:

Deputy Head of department Certification Body

Signature:  
(for printed version)

Date:

2021-06-08

1. This certificate and schedule may only be reproduced in full.
2. This certificate is not transferable and remains the property of the issuing body.
3. The Status and authenticity of this certificate may be verified by visiting [www.iecex.com](http://www.iecex.com) or use of this QR Code.



Certificate issued by:

**IBExU Institut für Sicherheitstechnik GmbH**  
Fuchsmühlenweg 7  
09599 Freiberg  
Germany



# IECEX Certificate of Conformity

Certificate No.: **IECEX IBE 20.0031X**

Page 2 of 3

Date of issue: 2021-06-08

Issue No: 0

Manufacturer: **Endress + Hauser Wetzer GmbH & Co. KG**  
Obere Wank 1  
87484 Nesselwang  
Germany

Additional  
manufacturing  
locations:

This certificate is issued as verification that a sample(s), representative of production, was assessed and tested and found to comply with the IEC Standard list below and that the manufacturer's quality system, relating to the Ex products covered by this certificate, was assessed and found to comply with the IECEX Quality system requirements. This certificate is granted subject to the conditions as set out in IECEX Scheme Rules, IECEX 02 and Operational Documents as amended

#### STANDARDS :

The equipment and any acceptable variations to it specified in the schedule of this certificate and the identified documents, was found to comply with the following standards

**IEC 60079-0:2017** Explosive atmospheres - Part 0: Equipment - General requirements  
Edition:7.0

**IEC 60079-11:2011** Explosive atmospheres - Part 11: Equipment protection by intrinsic safety "i"  
Edition:6.0

**IEC 60079-15:2017** Explosive atmospheres - Part 15: Equipment protection by type of protection "n"  
Edition:5.0

**IEC 60079-7:2017** Explosive atmospheres - Part 7: Equipment protection by increased safety "e"  
Edition:5.1

This Certificate **does not** indicate compliance with safety and performance requirements other than those expressly included in the Standards listed above.

#### TEST & ASSESSMENT REPORTS:

A sample(s) of the equipment listed has successfully met the examination and test requirements as recorded in:

Test Report:

[DE/IBE/ExTR21.0025/00](#)

Quality Assessment Report:

[DE/TUN/QAR06.0009/09](#)



# IECEX Certificate of Conformity

Certificate No.: **IECEX IBE 20.0031X**

Page 3 of 3

Date of issue: 2021-06-08

Issue No: 0

## **EQUIPMENT:**

Equipment and systems covered by this Certificate are as follows:

The NAMUR Switch Isolating Amplifiers Type RLN22-xx\*\* are used for the intrinsically safe and galvanically isolated operation of proximity switches with NAMUR behaviour or potential-free switches and resistance-connected switches. They are equipped with a 24 V voltage supply. The equipment is provided for installation in zone 2 or in the safe area as associated apparatus. The intrinsically safe signal circuits may be routed into areas that require EPL Ga (Zone 0) or Da (Zone 20).

The voltage difference between input and output circuit or supply can be up to 375 V peak. The modules are equipped with a circuit for the detection of line faults.

The technical data are mentioned in the Annex.

## **SPECIFIC CONDITIONS OF USE: YES as shown below:**

- The NAMUR Switch Isolating Amplifiers have to be installed in a suitable housing fulfilling the requirements of IEC 60079-7 or another recognized type of protection. The housing has to maintain a degree of protection of at least IP54 according to IEC 60529 for operation in zone 2.
- Connecting and disconnecting of non-intrinsically safe circuits are not allowed in energized state of the NAMUR Switch Isolating Amplifier.
- The DIP switches may only be operated when no explosive atmosphere is present.

## **Annex:**

[Annex\\_IBE20.0031\\_00.pdf](#)



# IECEX Certificate of Conformity - Annex



Certificate No: IECEx IBE 20.0031X

Issue No: 0

Date of Issue: 2021-06-08

Page 1 of 2

## Technical data:

Environmental data	
Ambient temperature range	-40 °C up to +60 °C
Degree of protection of the enclosure	≥ IP20

Electrical data			
1.	<b>Power Supply (1.1 and 1.2) and TBUS</b>		
	rated voltage range	$U_n$	24 V DC (19.2 ... 30 V DC)
	supply current	$I_n$	< 35 mA (24 V)
	power consumption	$P_n$	< 1 W
	maximum direct voltage	$U_m$	125 V DC
	maximum effective value of alternating voltage	$U_m$	253 V DC
	galvanically separated up to a peak voltage	$U_p$	375 V
2.	<b>Intrinsically safe sensor circuit (4.1 and 4.2/ 5.1 and 5.2)</b>		
	maximum output voltage	$U_o$	9.6 V
	maximum output current	$I_o$	10 mA
	maximum output power	$P_o$	25 mW
	effective internal capacity	$C_i$	11 nF
	effective internal inductivity	$L_i$	negligible
3.	<b>Relay output (2.1 and 2.2 / 3.1 and 3.2)</b>		
	maximum Switching voltage	$U_s$	250 V AC (2 A) / 120 V DC (0,2 A) / 30 V DC (2 A)
	maximum switching power	$P_s$	500 VA

For circuits including inductances and capacitances the following has to be observed:

The values for  $L_o$  and  $C_o$ , mentioned in this certificate are allowed for:

- distributed inductances and capacitances, e.g. as in a cable or
- if the total  $L_i$  of the external circuit (excluding the cable) is < 1 % of the  $L_o$  value or
- if the total  $C_i$  of the external circuit (excluding the cable) is < 1 % of the  $C_o$  value.

	Ex ia IIC	Ex ia IIB/IIIC	Ex ia IIA, Ex ia I
$C_o$	3.6 $\mu$ F	26 $\mu$ F	210 $\mu$ F
$L_o$	300 mH	1000 mH	1000 mH



# IECEX Certificate of Conformity - Annex



Certificate No: IECEx IBE 20.0031X

Issue No: 0

Date of Issue: 2021-06-08

Page 2 of 2

The values of  $L_0$  and  $C_0$ , mentioned in this certificate shall be reduced to 50 % or taken from the following table if both of the following conditions are met:

- the total  $L_i$  of the external circuit (excluding the cable) is  $\geq 1\%$  of the  $L_0$  value and
- the total  $C_i$  of the external circuit (excluding the cable) is  $\geq 1\%$  of the  $C_0$  value.

	Ex ia IIC					Ex ia I, Ex ia IIB/IIA, Ex ia			
$C_0$	500 nF	570 nF	590 nF	590 nF	600 nF	1 $\mu$ F	1 $\mu$ F	1 $\mu$ F	1 $\mu$ F
$L_0$	100 mH	50 mH	5 mH	1 mH	10 $\mu$ H	100 mH	5 mH	1 mH	10 $\mu$ H

The reduced capacitance of the external circuit (including cable) shall not be greater than 1  $\mu$ F for Groups I, IIA and IIB and 600 nF for Group IIC.